


Wi-Fi Smart Switch MK1




User Manual

Content

Introduction	01
Specification	03
Wiring Instruction	03
Power off	03
Wiring	04
Download the smart Life APP	06
Add Device	06
Install the MINI Extreme in the mounting box	10
Functions	10
Scan the code to see the detailed product manual	13

Introduction



Button Statements:

1. Single press: Turn on/off the smart device;
2. Press and hold for 5 seconds: Enter the pairing mode

Indicator:

Red indicator flash: The device is in the pairing mode.

Blue indicator steady on: 1. Normal connection with the gateway;
2.If no connection, then is in the low-power mode.
If the indicator light is off, it means the device is powered off.
On the App, the indicator is set to be steady on.

Terminal Statements:

Lin: Connect the live wire of the input port;
Lout: Connect the live wire of the load port;
N: Connect the neutral wire;
S1&S2: Connect the wires of the common switch.

Note:The illustrations of the products, accessories, and user interfaces in this manual are schematic diagrams for reference only. Probably there are slight difference between the actual product and the diagram due to the update and upgrade, please refer to the actual product.

Specification

Product Name: Wi-Fi Smart Switch
Model: MK1
Input: 100-250V~ 50/60Hz 10A MAX μ
Output: 100-250V~ 50/60Hz 10A MAX μ Resistive Load
LED: 150W Max@100V/300W Max@250V
Working Temperature: -10°C~35°C
Wireless Connectivity: WiFi 2.4GHz 802.11b/g/n
Frequency Range: 2400-2483.5 MHz
Wi-Fi/Bluetooth Max. Transmitting Power: 20 dBm
Compatible with Android 5.0 & iOS 9.0 or above



Wiring Instruction

Power off



Warning:Please install and maintain the device by a professional electrician. To avoid electric shock hazard, do not operate any connection or contact the terminal connector while the device is powered on!

Wiring



Note:

1. The device can be controlled automatically or via APP even if the terminals of S1 & S2 connect the switch or not.
2. It is prohibited to connect S1 and S2 terminals to the neutral or ground wire, in order to avoid damaging the equipment and causing danger.
3. Make sure all wires are connected correctly.

Download the smart Life APP

Scan the QR code as below or search for "Smart Life" in the APP store to download the Smart Life APP; Users who have installed the Smart Life APP will be directed to the device connecting page.




Add Device

Network Pairing Method 1: Automatically discover the network and pair.

- ① Tap the icon of the "Bluetooth", "WiFi" and "Location" on the smartphone (should connect WiFi 2.4GHz);
- ② Open the Smart Life APP and log in (if no account, pls register an account at first);


③ Long press the button, the red indicator flashes and enter into the network pairing mode;

④ Tap "+" on the top right of the APP home page, enter the page "Add Device";




⑤ Discover the device waiting for being added, click it and add it;

⑥ Connect the WiFi, log in the WiFi account with the password, then click "Next";




⑦ Waiting for the connection of the smartphone and the device, if connect successfully, will display "Added Successfully", then click "Done", will enter into the device interface.



09

Install the MINI Extreme in the mounting box



Functions

Remote Control: Remote control the smart switch via the APP on the smartphone;
Intelligent Control: Automatically control the switch based on the set scene;

10

Voice Control: Use simple voice commands with Alexa or Google Assistant to control your connected devices;
Countdown: Set the countdown time to open/close the device;
Timer: Set a certain time to control the on/off status of the connected device, can set several time groups, weekly cycle is possible;
Circulate: Set a time period, then set a certain time within the time period to turn on or off, then set the on/off time as the weekly circle time points;
Random: Set a time period, then set the device to turn on or off randomly within the time period;
Inching: Set a time period to shut down automatically after each time the device is started, avoiding the frequent countdown settings;
Astronomical: Set to turn on or off the device on or before the "Sunrise" or "Sunset". Relay Status Setting: Power-off, power-on, power off memory;

11

Anti-error Deletion: When remove the re-set function of the device hardware, the device enters into the network matching interface. If the linking is not reactivated during the network matching period (the matching time is out), the device will automatically connect to the matched router/gateway and retain the relevant parameters saved in the original device APP;
Child Lock: Prevent the child to trigger it unintentionally;
Light Mode: The indicator will be turned on or off according to the switch, the indicator will be off when close.
Factory Reset:

1. Press and hold the device button for 5 seconds;
2. Remove the device on the App and delete the data;
3. Quickly press the external switch 10 times (except for the external switch type, all other settings will be restored to factory defaults).

12

Scan the code to see the detailed product manual



13

WEEE Disposal and Recycling Information

All Products Bearing This Symbol are Waste Electrical and Electronic Equipment (WEEE as in Directive 2012/19/EU) Which Should Not Be Mixed with Unsorted Household Waste. Instead, You Should Protect Human Health and the Environment by Handing Over your Waste Equipment to a Designated Collection Point for the Recycling of Waste Electrical and Electronic.

Equipment Appointed by the Government or Local Authorities. Correct Disposal and Recycling will Help Prevent Potential Negative Consequences to the Environment and Human Health. Please Contact the Installer or Local Authorities for More Information About the Location as Well as Terms and Conditions of Such Collection Points.

14

Hereby, Orient Tech Limited declares that the radio equipment type MK1 is compliant with Directive 2014/53/EU.
The full text of the EU declaration of conformity is available at the following internet address:
<https://www.dqorient.com/downloads.html>

FCC Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and

15

(2) this device must accept any interference received, including interference that may cause undesired operation. This device and its antenna(s) must not be co-located or operating in conjunction with any other antenna or transmitter.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

16

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.
To maintain compliance with FCC's RF Exposure guidelines. This equipment should be installed and operated with minimum distance between 20cm the radiator your body: Use only the supplied antenna.

17



MADE IN CHINA 18